

Product Highlights

Easy expansion

Quickly add four USB 2.0 ports to any PC, allowing you to connect more peripherals with ease.

Sync and charge your iPad

Easily charge and sync your iPad at the same time on any of the USB ports.

Compact and portable

Fits easily into any bag for travel and can still function as a USB hub when without a power adapter.



DUB-H4

4-Port USB 2.0 Hub

Features

Connectivity:

- Four USB 2.0 ports
- Backwards compatible with USB 1.1

Fast Charge Mode¹:

- Four Fast Charge USB ports for high-power mobile devices such as an iPad
- Does not require a PC to charge devices

Easy To Use

- Plug and play
- Sleek, compact design
- Works on Windows, Mac, and Linux PCs

The D-Link DUB-H4 4-Port USB 2.0 Hub provides an easy way to add four USB 2.0 ports to your notebook or desktop computer. In Fast Charge Mode, each of the USB ports can provide a maximum charging current of 2.4 A for iPads, or 1.5 A for Battery Charging 1.2 compliant devices. This means you can charge devices like iPads while also connect additional USB devices like digital and web cameras, card readers, hard drives, mice, keyboards, printers, scanners, and other peripherals.

Add Four USB 2.0 Ports to Your Computer

With the DUB-H4 4-Port USB 2.0 Hub, you can conveniently add more USB 2.0 ports to any computer. Now you can connect up to four more USB peripheral devices – such as digital cameras, printers, external hard drives, mice, keyboards, flash drives, and tablet computers – to your notebook or desktop computer. USB 2.0 technology supports data rates of up to 480 Mbps, which means that you can enjoy faster transfer speeds compared to previous USB standards.

Fast Charge Your Devices

The DUB-H4 features four Fast Charge USB ports that are designed to provide an increased maximum charging current of 2.4 A to connected devices when the DUB-H4 is in Fast Charge Mode.¹ This makes it perfect for charging power-hungry mobile devices like the iPad, as these devices have high-capacity batteries that require higher charging currents to recharge quickly and effectively. The DUB-H4 does not require a PC to charge your devices, so you can take it with you on the road and leave your mobile device chargers at home.

Sync and Charge Your iPad Anywhere

The DUB-H4 lets you back up your iPad while giving it a full charge at the same time.² It is designed to fit into any notebook bag, and the compact size of the device will allow you to conveniently carry it with you wherever you go. Experience the freedom and convenience of portability and expandability with the D-Link DUB-H4 4-Port USB 2.0 Hub.

Plug and Play

Simply plug in the power adapter and connect the DUB-H4 to any PC. It's that easy - no drivers or software installation is required. Now you can connect up to four additional USB devices to your laptop, notebook, or desktop computer.

Technical Specifications		
Standards		
Standards	<ul style="list-style-type: none"> • USB specification version 2.0 (data rates of up to 480 Mbps) • USB specification version 1.1 (data rates of up to 12 Mbps) 	<ul style="list-style-type: none"> • OHCI • UHIC • EHCI
Interfaces	<ul style="list-style-type: none"> • Four USB Type A (female) downstream ports, white 	<ul style="list-style-type: none"> • Upstream USB Type B (female) port
Connectivity Rules	<ul style="list-style-type: none"> • Up to 127 devices • Up to five cascaded hubs 	
Minimum System Requirements	<ul style="list-style-type: none"> • Windows 10 / 8 / 7 / Vista / XP • Mac OS X 10.3 or above 	<ul style="list-style-type: none"> • Linux
Power LED	<ul style="list-style-type: none"> • Bus-powered (Blue): <ul style="list-style-type: none"> • Standard Charge Mode 	<ul style="list-style-type: none"> • Self-powered (Green): <ul style="list-style-type: none"> • Standard Charge Mode • Fast Charge Mode
Supplied Charging Current ¹	<ul style="list-style-type: none"> • Standard Mode: <ul style="list-style-type: none"> • 500 mA total for all USB ports 	<ul style="list-style-type: none"> • Fast Charge Mode¹: <ul style="list-style-type: none"> • Max. 1.5 A each for Battery Charging 1.2 compliant devices • Max. 2.4 A each for iPad / iPhone
Power Input	<ul style="list-style-type: none"> • 5 V / 2.5 A DC 	
General Specifications		
Temperature	<ul style="list-style-type: none"> • Operating: 0 to 40 °C (32 to 104 °F) 	<ul style="list-style-type: none"> • Storage: -20 to 60 °C (-4 to 140 °F)
Humidity	<ul style="list-style-type: none"> • Operating: 10% to 90% non-condensing 	<ul style="list-style-type: none"> • Storage: 5% to 95% non-condensing
Dimensions (L x W x H)	<ul style="list-style-type: none"> • 64 x 64 x 14 mm (2.52 x 2.52 x 0.55 inches) 	
Weight	<ul style="list-style-type: none"> • 85 g (0.19 lbs) 	
Certifications	<ul style="list-style-type: none"> • FCC • CE • C-Tick 	<ul style="list-style-type: none"> • IC • RoHS
Order Information		
<i>Part Number</i>	<i>Description</i>	
DUB-H4	DUB-H4 4-Port USB 2.0 Hub	

¹ The total combined power draw must be under 2.4 A or 12 W.

² D-Link provides a Windows utility for simultaneously syncing and charging iPads with 30-pin connectors.

Updated 12/07/16